

Robust Manual Call Point for Easy Mounting

RT 4



Certified



Flexible mounting



Robust enclosure



Different variants




Technical data

Operating voltage	24 V $\overline{=}$
Current input (in case of alarm)	7 mA
Line cross-section	$\leq 1.5 \text{ mm}^2$ (rigid)
Enclosure material	Zinc alloy die casting
Colour	Orange (~ RAL 2011)
Temperature	-5 °C – +40 °C
Relative humidity	20 % – 80 %, non-condensing
Protection rating	IP30
Dimensions (W x H x D)	131 x 133 x 34 mm

This certified SHE manual call point is used to manually trigger the alarm function of K + G Control Centres/Controls. It can be surface-mounted or mounted directly on flush-mounted junction boxes. Depending on the type of mounting, the cable entries from above/below or from behind can be used.

Variants

Type designation	Indicators and operating elements	Part number
RT 4-OR		8181 4101 0000
RT 4-OR-BS		8181 4100 0000
RT 4-OR-BS-AA		8181 4100 0100
RT 4-OR-BS-LT-A		8181 4100 1000
RT 4-OR-BS-LT-A-AA		8181 4100 1100



TECTRONIC

K + G Tectronic GmbH

In der Krause 48
52249 Eschweiler
Germany

+49 2403 99 500

info@kg-tectronic.de

